EPW 5000 Electric start



The EPW Series portable generators provide power where and when you need it. Portable generators can be used to power tools and provide emergency backup, as well as tackle site jobs and property improvement works, making it ideal for both work and recreational activities.

FEATURES

- Pramac OHV engine for maximum performance on all applications
- Electric and Recoil starting systems and Petrol fuel
- Low-oil level shutdown automatically safeguards engine from damage
- Engine oil for the first startup supplied in a bottle with the genset
- Digital multi meter tracks engine runtime for maintenance intervals
- Fuel gauge allows user to track gasoline levels
- Pratical Quick starting Instruction (QR code and Decal)
- AVR Automatic Voltage Regulator
- Schuko sockets and Battery Charger 12V DC
- Kit wheels integrated for easy transportation



PERFORMANCE		
Frequency	Hz	50
Voltage	V	230
Phase		1
Max Power	watt	4100
Rated Power	watt	4000




Engine		
Brand		Pramac
Type		OHV
Exhaust emission level		Stage V
Operating Speed Nominal	rpm	3000
Fuel		Petrol
Starting Systems		Electric (+Recoil)
Oil capacity	l	0.7
Low Oil Shutdown		√



Alternator		
Voltage regulation system		AVR
Protection	IP	23

Dimensional data		
Length	(L) mm	635
Width	(W) mm	662
Height	(H) mm	502
Dry weight	kg	61
Carton box dimension LxWxH	mm	685x535x475



Autonomy		
Fuel tank capacity		13
Fuel consumption 50%	l/h	1.62
Running time 50%	h	8



Noise level		
Guaranteed noise level (LWA)	dB(A)	97
Noise pressure level @ 7 m	dB(A)	65

Genset Control Panel

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.



Commands
- Engine On/Off switch
- Electric start



Instrumentation
- Voltmeter / Frequency meter / Hourmeter
- Fuel gauge (on fuel tank)
- 12V DC (Battery Charger)

Protections
- Magneto Thermal Circuit Breaker
- Low oil shutdown (Oil Guard)

SOCKET TYPE

SCHUKO 230V 16A IP44	2

The information is aligned with the Data file at the time of download.
Printed on 19/05/2025 (ID 20537)

©2024 | PR Industrial S.r.L unipersonale – Loc. Il Piano – 53031 Casole d'Elsa (SI) – ITALY. Company subject to the management and coordination of Generac Power Systems Inc.| All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice